

## LITTELFUSE SHOCK-BLOCK<sup>®</sup> LB100 GFCI LUNCHBOX

### LB100



#### Description

Littelfuse Shock-Block LB100GFCI Lunchbox was designed specifically for power distribution in the entertainment industry. It features heavy duty construction with hospital grade duplex GFCI outlets, recessed circuit breakers and indicator lights to ensure reliability.

Wet conditions, moisture or just worn cable insulation can cause ground faults that endanger the lives of those working on production sets. Whether you are shooting outdoors or around water, Littelfuse Shock-Block technology helps protect cast and crew.

#### Ordering Information

MODEL	CURRENT CAPACITY	VOLTAGE	PHASE	CONNECTION	DIMENSIONS	WEIGHT
LB100GFCI	100A	125VAC	Single	Bates Stage Pin	9.5"L x 8"W x 8.5"H	10 lbs.

#### Product Features

- Portable, in-line plug-in device
- Solid Bus-Bar Construction
- High Temp Wiring
- Heavy Duty Hardware

#### Specifications

**Voltage Rating:** 125VAC

**Input – Flow Thru:** 100A Stage Pin

**Output Type:** 5 – 20A Edison Duplex  
GFCI Receptacles

**Phase:** Single

**Enclosure:** Type 1

**Circuit Protection:** 5 – 20A 120V Circuit  
Breakers (10k AIC)

**Approval:** UL Listed

#### Web Resources

[www.littelfuse.com/shockblock](http://www.littelfuse.com/shockblock)

For more information, contact the Littelfuse Shock-Block Sales and Leasing Office at **818-764-7585**, or visit [www.littelfuse.com/shockblock](http://www.littelfuse.com/shockblock)